

# Listen to *Melodies of Prayer* without a computer ..

## BARIX Exstreamer 100



The **Barix Exstreamer 100** connects directly to the internet (without a computer), and allows you to hear **Melodies Of Prayer** on your regular stereo or headphone.

It also automatically reconnects to the internet broadcast after a power outage or any line interruption.

Here are the internet addresses for the **Melodies Of Prayer** broadcast:

MELODIES OF PRAYER	
Broadcast Stream IP Addresses & Ports	
STREAM	[IP ADDRESS]:[PORT]
64K	65.60.34.98:80
64K	67.212.189.122:8187
128K	99.198.109.149:80
128K	99.198.118.250:8152

*MelodiesOfPrayer.com*

## INSTALLATION INSTRUCTIONS:

1. Connect your headphone to the **headphone port** in the front of the BARIX.  
Or you can connect your stereo to the **LINE OUT ports** in the back of the BARIX.
2. Connect a LAN/internet cable from your hub/modem to the **LAN port** in the back of the BARIX.

*On the next steps, prepare to listen and write down the numbers being announced to you through your headphone/stereo speakers.*

*On the next step, when connected to the power source, the BARIX Exstreamer will immediately connect to your network and will announce 4 sets of numbers separated by dots. This is the IP address assigned by your network for your BARIX.*

*For example: 192.168.0.12  
(Voice: one-nine-two dot one-six-eight ... )*

3. Connect the power adapter jack to the **PWR port** in the back of the BARIX. Then plug the power adapter into an appropriate electric outlet.
4. Write down in the boxes below the IP Address of your BARIX ( 4 sets of numbers separated by dots that you heard announced through the speakers):

<input type="text"/>	.	<input type="text"/>	.	<input type="text"/>	.	<input type="text"/>
----------------------	---	----------------------	---	----------------------	---	----------------------

5. Now open your internet browser and type the above IP Address of your BARIX.

*( For example: 192.168.0.12 )*

*This will bring up the BARIX main settings page.*

6. Click on the **Config** link.  
*This will bring up the Device Configuration page.*
7. Click on the **STREAMING** link.
8. On the **Server IP Address**, type the IP Address of one of the Melodies Of Prayer Broadcast streams.  
*(see the Table above).*
9. On the **Server Port**, type the corresponding port for each stream's IP Address.

*For example:*

Server IP Address:	<input type="text" value="99"/>	.	<input type="text" value="198"/>	.	<input type="text" value="118"/>	.	<input type="text" value="250"/>
Server Port:	<input type="text" value="8152"/>						

10. Click **Apply**.

Now you are ready to listen to Melodies Of Prayer through your BARIX Exstreamer (without a computer).

*MelodiesOfPrayer.com*

*May Heaven's beauty, power and love fill your heart today*