

# Listen to *Melodies of Prayer* without a computer ..

## BARIX Exstreamer 100



The **Barix Exstreamer 100** connects directly to the internet (without a computer), and allows you to hear **Melodies Of Prayer** on your regular stereo or headphone.

It also automatically reconnects to the internet broadcast after a power outage or any line interruption.

Here are the internet addresses for the **Melodies Of Prayer** broadcast:

| MELODIES OF PRAYER                    |                     |
|---------------------------------------|---------------------|
| Broadcast Stream IP Addresses & Ports |                     |
| STREAM                                | [IP ADDRESS]:[PORT] |
| 64K                                   | 65.60.34.98:80      |
| 64K                                   | 67.212.189.122:8187 |
| 128K                                  | 99.198.109.149:80   |
| 128K                                  | 99.198.118.250:8152 |

*MelodiesOfPrayer.com*

## INSTALLATION INSTRUCTIONS:

1. Connect your headphone to the **headphone port** in the front of the BARIX.  
Or you can connect your stereo to the **LINE OUT ports** in the back of the BARIX.
2. Connect a LAN/internet cable from your hub/modem to the **LAN port** in the back of the BARIX.

*On the next steps, prepare to listen and write down the numbers being announced to you through your headphone/stereo speakers.*

*On the next step, when connected to the power source, the BARIX Exstreamer will immediately connect to your network and will announce 4 sets of numbers separated by dots. This is the IP address assigned by your network for your BARIX.*

*For example: 192.168.0.12  
(Voice: one-nine-two dot one-six-eight ... )*

3. Connect the power adapter jack to the **PWR port** in the back of the BARIX. Then plug the power adapter into an appropriate electric outlet.
4. Write down in the boxes below the IP Address of your BARIX ( 4 sets of numbers separated by dots that you heard announced through the speakers):

|                      |   |                      |   |                      |   |                      |
|----------------------|---|----------------------|---|----------------------|---|----------------------|
| <input type="text"/> | . | <input type="text"/> | . | <input type="text"/> | . | <input type="text"/> |
|----------------------|---|----------------------|---|----------------------|---|----------------------|

5. Now open your internet browser and type the above IP Address of your BARIX.

*( For example: 192.168.0.12 )*

*This will bring up the BARIX main settings page.*

6. Click on the **Config** link.  
*This will bring up the Device Configuration page.*
7. Click on the **STREAMING** link.
8. On the **Server IP Address**, type the IP Address of one of the Melodies Of Prayer Broadcast streams.  
*(see the Table above).*
9. On the **Server Port**, type the corresponding port for each stream's IP Address.

*For example:*

|                    |                                   |   |                                  |   |                                  |   |                                  |
|--------------------|-----------------------------------|---|----------------------------------|---|----------------------------------|---|----------------------------------|
| Server IP Address: | <input type="text" value="99"/>   | . | <input type="text" value="198"/> | . | <input type="text" value="118"/> | . | <input type="text" value="250"/> |
| Server Port:       | <input type="text" value="8152"/> |   |                                  |   |                                  |   |                                  |

10. Click **Apply**.

Now you are ready to listen to Melodies Of Prayer through your BARIX Exstreamer (without a computer).

*MelodiesOfPrayer.com*

*May Heaven's beauty, power and love fill your heart today*